



“X” — Circuit Closure
 “O” — Circuit Open

CAM CODE SELECTION CHART *

Contact ^{1,2} block	Number of Positions:		2-Positions					3-Positions				4-Positions				
	Turn Cam:	Configuration:	B	J	G	G	G	R	L	K	G	A	R	L		
		Orientation:	3	1	1	3	1	1	1	4	1	1	1	1		
	Push Cam Code:		YA	TC	BB	FB	TB	FB	MA	ED	MC	MD	BC	VB		
	Device Positions:		1 2	1 2	1 2	1 2	1 2	1 2	1 2 3	1 2 3	1 2 3	1 2 3	1 2 3 4	1 2 3 4		
Terminal	Condition															
	PTCC	1-2	Free Depress	OX OO	XO OO	OX OX	XX XO	OX OX	XX OX	XOO XOO	XXO XXO	OXX OXX	XOO OOO	XXXX OXXX	XOOO OOOO	
		3-4	Free Depress	OO XX	OO XX	XO XO	OO OX	XO XO	OO OX	OOO OOX	OOO OOX	XOO XOO	OXX OXX	OXX OXX	OOOO XOOO	OOOO XOOO
		5-6	Free Depress	XO OO	XO XO	XX XO	OX OX	XX OO	XX XO	OOX OOX	OOX OOX	XXO XOO	OXX OXO	OXX OXO	XXXX XXOX	OOXO OOOO
		7-8	Free Depress	OX OX	OO OX	OO OX	XO XO	OO XX	OO OX	OOO XOO	OOO XOO	OOX OOX	XOO XOO	OXX OXX	OXX OXX	OOOO OOXO
4-Plunger Adapter Kit ³ PTCA			For circuits below — Use 4 plunger adapter kit and at least 1 block from above													
	PTCC	1-2	Free Depress	— —	OX OO	XO OO	— —	XO OO	XX OO	OXO OXO	OXX OXX	XOX OOO	XOX XOO	XXXX XOXX	OXOO OOOO	
		3-4	Free Depress	XO XX	OO XX	OX XX	— —	OX XX	OO XX	— —	— —	OXX OXX	OOO OOX	OOO OOX	OOOO OXOO	OOOO OXOO
		5-6	Free Depress	XX OO	OX OX	— —	XO OO	XX XO	— —	— —	XOO XOO	XXX OXO	OXX OXX	OXX OXX	XXXX XXXO	OOOX OOOO
		7-8	Free Depress	OO XO	OO XO	— —	OX XX	OO OX	— —	OOO OXO	OOO OXO	— —	OXX XOX	OXX XOX	OOOO OOOX	OOOO OOOX